

Last updated: Jun 27, 2018

懶人包-Reset Default+F/W Upgrade

1. Download "upgradeAuto_Reboot.bin" file from the link below
https://drive.google.com/open?id=1RQLwjBlwevJfQ7TZa9_0dDyVoLjuyENC
2. Shut Down the DVR/NVR
3. Remove HDD and network cables. Only power cable, HDMI monitor, and mouse remained.
4. Pick one USB flash drive (Transcend and Sandisk are highly recommended)
5. Format this USB to FAT32 by a PC
6. Download the latest firmware. Please go to AVTECH official website to download. <http://www.avtech.com.tw/>
7. Extract the FW file, and get ".bin" files
8. Put "upgradeAuto_Reboot.bin" and the firmware files into the USB flash drive, and only these files.
9. Plug in the USB flash drive on the right USB port
10. Turn on the DVR/NVR
11. The upgrading process will show up on the screen, like this video
<http://vid1043.photobucket.com/albums/b436/avtecheagleeyes/b658a79a.mp4>
12. After upgrading, DVR/NVR will reboot, and work again with newer firmware

1. 從下面的連結下載"upgradeAuto_Reboot.bin"檔案
2. 將 DVR / NVR 關機
3. 拔除硬碟和網路線，僅剩電源線，HDMI線接螢幕，以及滑鼠
4. 拿一個USB隨身碟（請使用4GB以內或更小的隨身碟，強烈建議使用Transcend或Sandisk）
5. 通過電腦先將此USB格式化為FAT32
6. 下載最新的Firmware（查詢我們的官網，或詢問技術人員）
7. 下載後的Firmware檔，解壓縮後，得到另一份".bin"檔案
8. 將剛剛的"upgradeAuto_Reboot.bin"檔案，和這份Firmware檔案一起放到隨身碟裡（強烈建議隨身碟裡只有這些bin檔，沒有其它檔案）
9. 將隨身碟插到DVR/NVR上
10. 將 DVR / NVR 開機
11. 開機後有可能機器會停在全黑畫面3~5分鐘，此時正在進行更新程序
12. 升級好以後，DVR / NVR會再重開機一次，開機後再檢查一次Firmware版本若有進版就是成功了，若沒有，可以換USB插槽或換USB再試一次